

ALINCO DJ-193

Handy VHF 5 watts

Technical data: Frequency range 135-175MHz (Extended for PG + HG) Harmonize step 5/10/12,5/15/20/25/30kHz
Modulation FM (F3E) Power supply 6.0 - 16,0 V DC Dimension 56x40x124mm (W/D/H w.EPB-48N) Weight 375 g
(complete with EPB-48N) Operating temperature -20°C to 60°C Input energy (6V) TX Hi 1.2A RX 200mA SAVE 50mA
Receiver: Intermediate frequency 21,7MHz/450kHz Sensitivity -14dBu(144-148MHz)/-12dBu(135-174MHz)
Selectivity more -6dB(12kHz)/less -60dB(26kHz) Audio output power @ 10% THD 280mW @ 8ohm Transceiver: PowerHi
(13.8V) 5W Lo 0.8W Frequency stroke +/- 5.0kHz